



Four scene switch - 4

Model: AU-XSS4



Compact Size



Multiple
Actions



Fast
Response



No Wiring



Rechargeable
Battery

INTRODUCTION

The AutronX 4-Button Smart Scene Switch is a wireless battery-operated controller designed for convenient and flexible smart home operation. Operating through the ZigBee 3.0 protocol, it allows users to trigger customized scenes and control connected smart devices with a single touch. The switch includes **4 programmable buttons**, and each button supports **Single Click, Double Click, and Long Press** actions, enabling up to **12 configurable actions** from a single device.

TECHNICAL SPECIFICATIONS

Model	: AU-XSS4
Product Name	: Four Scene Switch
Battery Type	: Lithium Battery 3.7V / 150mAh
Charging Interface	: Type-C charging
Max. Range	: Up to 25 m (Open Area)
Wireless Protocol	: Zigbee 3.0
Control Actions	: Single Click Double Click Long Press >3Sec
Total Actions	: 12 Action
Battery Life	: Up to 1 Year* (Depend on usage)
Operating Temperature	: -10°C to +50°C
Product Dimensions	: 86 × 86 × 10 mm

Features

ZigBee 3.0 Wireless Communication

Wireless operation through ZigBee protocol with Hub connectivity.

Battery Operated

Built-in rechargeable lithium battery for cable-free operation.

4 Programmable Buttons

Four independent buttons for flexible smart control.

12 Configurable Actions

Supports Single Click, Double Click, and Long Press on each button.

One-Touch Scene Activation

Trigger customized smart scenes instantly.

App Configuration

Easy setup and scene assignment through AutronX Smart App / Smart Life App.

FUNCTION AND WORKING

1. The switch communicates wirelessly through the ZigBee Hub/Gateway.
2. Each button supports three configurable actions:
 - Single Click
 - Double Click
 - Long Press (>3 seconds)
3. Users can assign different scenes or device controls to each action.
4. Example:
 - Single Click → Turn ON all lights
 - Double Click → Turn OFF all lights
 - Long Press → Activate custom scene
5. Once a button is pressed, the switch sends the command to the ZigBee Hub, and the configured scene executes instantly.

NETWORK & CONFIGURATION SETUP

1. Open the **Smart Life / AutronX Smart App** and ensure the **ZigBee Hub** is online.
2. Insert a **pin (<3 mm dia.)** into the **reset hole located on the side of the switch**.
3. Press and hold for **5 seconds** until the **Green LED blinks**, indicating pairing mode.
4. Open the configured **ZigBee Hub** and select the **ZigBee Device** option.
5. Tap **Add Device** to start searching for new ZigBee devices.
6. The hub will search for approximately **10–120 seconds** until the device appears.
7. Select the detected **4-Button Smart Scene Switch** and complete pairing.
8. Configure button actions and assign scenes as required.